



### In the Box:



BATTERYPACK4



CALL POINT RESET KEY

### PRODUCT INFORMATION:

- Upto 3 years Battery Life
- Category One radio module
- CE ROHS & EMC Compliant
- Battery Low indication
- Secure Reset Function
- Totally wire free operation
- Combined Sounder and Strobe
- Mesh Radio connectivity
- Radio Frequency 869Mhz
- 2Km line of sight range
- Status LED
- Radio Frequency 869Mhz
- 2Km line of sight range
- Status LED

|                             |                               |
|-----------------------------|-------------------------------|
| <b>Product Code:</b>        | <b>FMCEVASYNP1</b>            |
| <b>IP Rating:</b>           | <b>IP55</b>                   |
| <b>Total Weight:</b>        | <b>1.65KG</b>                 |
| <b>Overall Dimmensions:</b> | <b>H 350 X W 163 X D 98MM</b> |
| <b>Sound Output (dB)</b>    | <b>110dB (at 1 meter)</b>     |