



EN54 Compliant Call Point

In the Box:



4.5 TRANSFORMER



CALL POINT RESET KEY

PRODUCT INFORMATION:

- Mains Powered Only
- Screen resolution: 480×272
- Connect 250 Devices
- Secure Pairing
- First Aid Call function
- System Status Indication
- Engineers Mode
- Supervisors Mode
- 85dB Buzzer
- Fast Pair (V3 Software version only)
- Auto Site Reset Function
- Mesh Radio connectivity
- Radio Frequency 869Mhz
- Zoning Function
- Optional Battery Backup (Separate Device)
- Colour coded squares for easy device identification
- Manual Call Point for easy Activation
- Wall or Desk Mount Configuration

Product Code:	FMCEVASYNP2
IP Rating:	Indoor Only
Total Weight:	1KG
Overall Dimmensions:	H 225 X W 166 X D 75MM
Sound Output (dB)	85dB